

IQxel™ Next Generation Connectivity Test System



General Technical Specifications

RF Analyzer

| Parameter | Ports | Value | |
|---------------------------|----------|--|---|
| Input frequency range | RF1, RF2 | 860 to 960 MHz 1770 to 2100 MHz 2200 to 2600 MHz 4900 to 6000 MHz | |
| IF bandwidth | RF1, RF2 | IQxel-80 | 120 MHz |
| | | IQxel-160 | (120 + 120) MHz |
| Max input power | RF1, RF2 | +30 dBm peak +25 dBm average | |
| Input power accuracy | RF1, RF2 | Specification: | ± 0.75 dB (+20 to -75 dBm) |
| | | Typical: | ± 0.50 dB (+20 to -75 dBm) |
| Quantization | | 16 bits | |
| Input return loss | RF1, RF2 | > 12 dB (> 1 GHz) | |
| Spurious | RF1, RF2 | < -55 dBc (50 kHz RBW) (CW) | |
| Spectral flatness | RF1, RF2 | Specification: | $\leq \pm 0.50$ dB (+/- 40 MHz, > 1 GHz) $\leq \pm 0.50$ dB (+/- 8 MHz, < 1 GHz) |
| | | Typical: | $\leq \pm 0.25$ dB (+/- 40 MHz, > 1 GHz) $\leq \pm 0.25$ dB (+/- 8 MHz, < 1 GHz) |
| Inherent spurious floor | RF1, RF2 | ≤ -90 dBm | |
| Noise figure | | ≤ 30 dB at minimum input attenuation | |
| Integrated phase noise | | < 0.5 degrees (100 Hz to 1 MHz) 0.3 degrees (100 Hz to 1 MHz) typical | |
| Signal to noise ratio | | ≥ 55 dB 100 kHz RBW | |
| Sampling data rate | | 10, 20, 40, 80, 160 MHz | |
| Waveform capture duration | | at 10 MHz sampling data rate | 3200 ms |
| | | at 20 MHz sampling data rate | 1600 ms |
| | | at 40 MHz sampling data rate | 800 ms |
| | | at 80 MHz sampling data rate | 400 ms |
| | | at 160 MHz sampling data rate | 200 ms |

RF Analyzer — Signal Trigger

| Parameter | Range | |
|----------------------------|------------------------------------|---------|
| Absolute minimum value | Wideband RF | -30 dBm |
| | Video | -40 dBm |
| Absolute maximum value | Limited by the maximum input power | |
| Trigger relative threshold | 30 dB | |
| Level accuracy | < +/- 2 dB | |

Baseband Analyzer

| Parameter | Port Designations | Range |
|---------------------|----------------------------------|---------------------------|
| Input power range | BBA_I+, BBA_I- BBA_Q+, BBA_Q- | 2 V peak-to-peak |
| Common mode voltage | BBA_I+, BBA_I- BBA_Q+, BBA_Q- | 0 V (DC coupled) |
| Impedance | BBA_I+, BBA_I- BBA_Q+, BBA_Q- | 50 Ω (100 Ω differential) |

RF Generator

| Parameter | Ports | Range | |
|---------------------------|----------|--|--|
| Output frequency range | RF1, RF2 | 860 to 960 MHz 1770 to 2100 MHz 2200 to 2600 MHz 4900 to 6000 MHz | |
| IF bandwidth | RF1, RF2 | IQxel-80 | 120 MHz |
| | | IQxel-160 | (120 + 120) MHz |
| | | CW: | +9 to -95 dBm (1700 to 2100 MHz), P1dB +9 to -95 dBm (2200 to 2600 MHz), P1dB +7 to -95 dBm (4900 to 6000 MHz), P1dB |
| Output power accuracy | | Specification: | ± 0.75 dB (0 to -95 dBm, with ALC ¹) |
| | | Typical: | ± 0.50 dB (0 to -95 dBm) |
| Quantization | | 16 bits | |
| Output return loss | RF1, RF2 | > 12 dB (> 1 GHz) | |
| Spurious (in channel) | RF1, RF2 | Specification: | ≤ -50 dBc or ≤ -95 dBm (80 MHz) |
| Spurious (out of channel) | RF1, RF2 | Out-of-band (>± 40 MHz from carrier): | ≤ -45 dBc |

¹Automatic Level Control (ALC) enables the internal power detector to be used for power level feedback.

| | | | |
|---|----------|---|---|
| Spectral flatness | RF1, RF2 | Specification: | $\leq \pm 0.50$ dB (+/- 40 MHz, > 1 GHz) $\leq \pm 0.50$ dB (+/- 8 MHz, < 1 GHz) |
| | | Typical: | $\leq \pm 0.25$ dB (+/- 40 MHz, > 1 GHz) $\leq \pm 0.25$ dB (+/- 8 MHz, < 1 GHz) |
| Integrated phase noise | | < 0.5 degrees (100 Hz – 1 MHz) 0.3 degrees (100 Hz – 1 MHz) typical | |
| Signal to noise ratio | | Specification: | ≥ 60 dB 100 kHz RBW, minimum attenuation, power level = -45 dBm |
| | | Typical: | ≥ 70 dB (100 kHz RBW), power level = -45 dBm |
| Carrier leakage | | ≤ -45 dBc (CW output) ≤ -90 dBm (between packets, when enhanced gap rejection enabled) | |
| Gap power | | ≤ -90 dBm/100kHz | |
| Sampling data rate | | 10, 20, 40, 80, 160 MHz | |
| Waveform playback duration (non-repeat) | | at 10 MHz sampling data rate | 3200 ms |
| | | at 20 MHz sampling data rate | 1600 ms |
| | | at 40 MHz sampling data rate | 800 ms |
| | | at 80 MHz sampling data rate | 400 ms |
| | | at 160 MHz sampling data rate | 200 ms |

Baseband Generator

| Parameter | Port Designations | Range |
|---------------------|----------------------------------|---|
| Output power range | BBG_I+, BBG_I- BBG_Q+, BBG_Q- | 2 V peak-to-peak |
| Common mode voltage | BBG_I+, BBG_I- BBG_Q+, BBG_Q- | 0 V (DC coupled) |
| Impedance | BBG_I+, BBG_I- BBG_Q+, BBG_Q- | 50 Ω (100 Ω differential) |

Port Isolation

| | |
|----------------------|-----------------|
| VSA to VSG isolation | > 80 dB typical |
|----------------------|-----------------|

Timebase

| | |
|---|--|
| Oscillator type | OCXO |
| Frequency | 10 MHz |
| Initial accuracy (25°C, after 60 minute warm-up) | < +/- 0.05 ppm |
| Maximum aging | < +/- 0.1 ppm per year |
| Temperature stability | < +/-0.05 ppm over 0°C to 50°C range, referenced to 25°C |
| Warm-up time (to within +/-0.1 ppm at 25°C) | < 30 minutes |

Wireless LAN (802.11a/b/g/n/p/ac) Measurement Specifications

| Measurement | Description | Performance |
|---------------------|---|--|
| EVM | EVM averaged over payload based on standard requirements | <p>(Averaged over 20 packets, 16 data OFDM symbols long)</p> <p>Full packet channel estimation Residual VSA EVM: ≤ -45 dB (+20 to -20 dBm) ≤ -43 dB (-20 to -25 dBm) ≤ -38 dB (-25 to -30 dBm) Residual VSG EVM: ≤ -45 dB (-5 to -45 dBm)</p> <p>Preamble only channel estimation Residual VSA EVM: ≤ -42 dB (+20 to -20 dBm) ≤ -40 dB (-20 to -25 dBm) ≤ -35 dB (-25 to -30 dBm) Residual VSG EVM: ≤ -42 dB (-5 to -45 dBm)</p> <p>Note: 80 MHz 802.11ac waveform, measured system loopback</p> |
| Peak power | Peak power over all symbols (dBm) | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) |
| RMS power | All: average power of complete data capture (dBm) | |
| | No gap: average power over all symbols after removal of any gap between packets (dBm) | |
| Max avg power | Peak value of the amplitude as a moving average over 40 samples (dBm) | |
| I/Q amplitude error | I/Q amplitude imbalance (%) and approximate contribution to EVM (dB) | <p>Residual VSA I/Q imbalance: ≤ 1% (+20 to -35 dBm)</p> <p>Residual VSG I/Q imbalance: ≤ 1% (-5 to -70 dBm)</p> |

| Measurement | Description | Performance | |
|---|---|--|-----------|
| I/Q phase error | I/Q phase imbalance (degrees) and approximate contribution to EVM (dB) | Residual VSA I/Q imbalance: ≤ 0.5 degree (+20 to -35 dBm) Residual VSG I/Q imbalance: ≤ 0.5 degree (-5 to -70 dBm) | |
| Frequency error | Carrier frequency error (kHz) | (For 802.11n packet at 16 symbols, EVM better than -25 dB) VSA measurement error: ≤ ± 0.2 ppm calibrated | |
| RMS phase noise | Integrated phase noise (degrees) | VSA integrated phase noise: < 0.5 degrees (100 Hz to 1 MHz) (2200 to 2600 MHz) < 0.5 degrees (100 Hz to 1 MHz) (4900 – 6000 MHz) | |
| PSD | Power spectral density (dBm/Hz) versus frequency offset center frequency ± 40 MHz | | |
| Spectral mask | Transmit spectrum mask | IQxel-80 | ± 120 MHz |
| | | IQxel-160 | ± 240 MHz |
| Spectral flatness | Reflects variation of signal energy as a function of OFDM subcarrier number 802.11a/g OFDM signals only | VSA flatness over ≤ 80 MHz Ch BW: ± 0.5 dB | |
| Sidelobe analysis (spectral mask, LO leakage) | Center peak and peaks of 1st and 2nd upper/lower sidelobes (dB) 802.11b/g DSSS signals only | | |
| CCDF (complementary cumulative distribution function) | Probability of peak signal power being greater than a given power level versus peak-to-average power ratio (dB) | | |
| Power on / power down ramp | On: relative power level (% of average) versus time (802.11b/g CCK signals only) Power-on time from 10% to 90% Power-on time from 90% power level to start of packet (Not provided for 802.11a/g OFDM signals) Off: relative power level (% of average) versus time (802.11b/g CCK signals only) Power-on time from 10% to 90% Power-on time from 90% power level to start of packet (Not provided for 802.11a/g OFDM signals) | | |
| Eye diagram | I and Q channels versus time (802.11b/g DSSS signals only) | | |
| PSDU data | Recovered binary data sequence, including the MAC header and Frame Check Sequence, if present | | |
| Raw capture data | I and Q signals versus time | | |

| Measurement | Description | Performance |
|---------------------------|--|-------------|
| General waveform analysis | DC offset, RMS level, minimum/maximum amplitude, peak-to-peak amplitude, RMS I- and Q-channel levels | |
| CW frequency analysis | Frequency of CW tone | |

Bluetooth® (1.0, 2.0, 2.1, 3.0) Measurement Specifications

| Measurement | Description | Performance |
|--------------------------------------|---|---|
| TX output power | Transmit DUT output power (dBm) | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) ± 0.50 dB (+20 to -35 dBm) typical |
| TX output spectrum | Transmit DUT power spectral density | |
| 20 dB bandwidth | Bandwidth between the +/- 20 dB down points of the modulation waveform | VSA frequency accuracy: ≤ ± 0.2 ppm calibrated |
| In-band emissions (Adjacent channel) | Spurious emission measured at +/- 5 MHz of DUT TX frequency only | VSA spurious: < -50 dBc (50 kHz RBW) (CW) |
| Modulation characteristics | Average and peak frequency deviation (Hz) | (For EVM better than -25 dB) VSA measurement error: ≤ ± 0.2 ppm calibrated |
| Carrier frequency tolerance | Carrier frequency offset (Hz) | |
| Carrier frequency drift | Carrier frequency change over the Bluetooth burst (Hz) | |
| Relative transmit power (EDR) | Average power of complete data capture (dBm) | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) |
| Carrier frequency stability (EDR) | Frequency drift over the Bluetooth EDR burst duration (Hz) | |
| Receive sensitivity ¹ | Receive sensitivity test using LitePoint or user-generated waveforms. Includes Dirty Packets. | VSG power accuracy: ± 0.75 dB (+ 5 to -95 dBm) |
| Maximum input signal level | Assuming single-ended BER measurement | |
| RMS EVM (EDR) | RMS EVM for Bluetooth EDR | Residual VSA EVM: ≤ -35 dB (+20 to -25 dBm) |
| Peak EVM (EDR) | Peak EVM for Bluetooth EDR | Residual VSG EVM: ≤ -35 dB (-5 to -70 dBm) |

¹ IQxel supports testing sensitivity with Dirty Packets

Bluetooth (4.0, 4.1, 4.2) Measurement Specifications

| Measurement | Description | Performance |
|--|--|---|
| Output power at NOC ¹ | | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) |
| Output power at EOC ¹ | | |
| In-band emissions at NOC ¹ | Spurious emission measured at +/- 5 MHz of DUT TX frequency only | VSA spurious: < -50 dBc (50 kHz RBW) (CW) |
| In-band emissions at EOC ¹ | | |
| Modulation characteristics | Average and peak frequency deviation (Hz) | VSA frequency accuracy: ≤ ± 0.2 ppm calibrated |
| Carrier frequency offset and drift at NOC ¹ | Carrier frequency offset (Hz) and change over the Bluetooth burst (Hz) | |
| Carrier frequency offset and drift at EOC ¹ | | |
| Receiver sensitivity at NOC ^{1,2} | Receive sensitivity test using LitePoint or user-generated waveforms | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) |
| Receiver sensitivity at EOC ^{1,2} | | |
| C/I and receiver selectivity performance ³ | | VSA spurious: < -50 dBc (50 kHz RBW) (CW) |
| Blocking performance ³ | | |
| Intermodulation performance | | |
| Maximum input signal level | Assuming single-ended BER measurement | VSG maximum output power: +9 to -95 dBm CW 0 to -95 dBm modulated |
| PER report integrity | Verifies the DUT PER report mechanism | |

1 NOC and EOC tests are the same except for the operating conditions which do not impact the test equipment requirements

2 External signal source required for these measurements (not LitePoint supplied)

3 IQxel provides the wanted signal only. No interfering signal is available

Bluetooth 5 Measurement Specifications

Bluetooth 5 introduced a couple of new test requirements:

Data Rate: New requirements for testing with 2 Mbps, 1 Mbps, 500 kbps, 125 kbps signal

Stable Modulation: Optional requirement for device to support smaller variation in the frequency deviation during modulation (modulation index between 0.495-0.505). This enhancement gives device stable and better range coverage and thus competitive advantage

| Measurement | Description | Performance |
|--|--|--|
| In-band emissions | Spurious emission measured at ± 5 MHz of DUT TX frequency only. Tested at 1 Mbps, 2 Mbps | VSA spurious: < -50 dBc (50 kHz RBW) (CW) |
| Modulation Characteristics | Average and peak frequency deviation (Hz). Tested at 1 Mbps, 2 Mbps, 125 kbps | VSA frequency accuracy: $\leq \pm 0.2$ ppm calibrated |
| Carrier Frequency offset and drift | Carrier frequency offset (Hz) and change over the Bluetooth burst (Hz). Tested at 1 Mbps, 2 Mbps, 125 kbps | |
| Stable Modulation Characteristics | Tested at 1 Mbps, 2 Mbps | VSA frequency accuracy: $\leq \pm 0.2$ ppm calibrated |
| Receiver Sensitivity | Receive sensitivity test using LitePoint or user-generated waveforms. Tested at 1 Mbps, 2 Mbps, 125 kbps | VSG power accuracy: ± 0.75 dB (0 to -95 dBm) |
| Receiver Sensitivity – Stable Modulation Index | Tested at 1 Mbps, 2 Mbps, 500 kbps, 125 kbps | |
| Maximum Input signal level | Assuming single-ended BER measurement. Tested at 1 Mbps, 2 Mbps | VSG maximum output power: 0 to -95 dBm |
| Maximum Input signal level – Stable Modulation Index | Tested at 1 Mbps, 2 Mbps | |
| C/I and Receiver Selectivity Performance | Tested at 1 Mbps, 2 Mbps, 500 kbps, 125 kbps | VSA spurious: < -50 dBc (50 kHz RBW) (CW) |
| Blocking Performance | Tested at 1 Mbps, 2 Mbps | |
| Intermodulation Performance | Tested at 1 Mbps, 2 Mbps | |
| PER Report Integrity | Verifies the DUT PER report mechanism. Tested at 1 Mbps, 2 Mbps, 500 kbps, 125 kbps | |

ZigBee (802.15.4)

| Measurement | Description | Performance |
|--|---|---|
| Output power | Transmit DUT output power (dBm) | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) ± 0.50 dB (+20 to -35 dBm) typical |
| Power spectral density | Transmit DUT power spectral density | |
| Center Frequency Tolerance | Tx center frequency tolerance | VSA frequency accuracy: ≤ ± 0.2 ppm calibrated |
| EVM | Offset: compensate the I and Q offset in OQPSK Normal: no compensation applied | |
| Other modulation quality measurements | LO leakage, clock error, phase error, symbol clock error | |
| CCDF (complementary cumulative distribution function) | Probability of peak signal power being greater than a given power level versus peak-to-average power ratio (dB) | |

Z-Wave (ITU-T G.9959)

| Measurement | Description | Performance |
|--------------------------|-----------------------------------|---|
| Output Power | TX output power (dBm) | VSA power accuracy: +/- 0.75 dB (+20 to -35 dBm) +/- 0.50 dB (+20 to -35 dBm) typical |
| Power Spectral Density | TX power spectral density | |
| Carrier Frequency Offset | TX center frequency error | VSA frequency accuracy: ≤ +/- 0.2 ppm calibrated |
| Frequency Deviation | RMS, Min, Max Frequency Deviation | |
| Symbol Clock Error | Symbol Clock Error and Jitter | |
| RX Power Level | RF Generator Output Level Range | VSG output power: +9 to -95 dBm CW 0 to -95 dBm modulated |

WiSUN MR-FSK (802.15.4g)

| Measurement | Description | Performance |
|--------------------------|-----------------------------------|---|
| Output Power | TX output power (dBm) | VSA power accuracy: +/- 0.75 dB (+20 to -35 dBm) +/- 0.50 dB (+20 to -35 dBm) typical |
| Power Spectral Density | TX power spectral density | |
| Carrier Frequency Offset | TX center frequency error | VSA frequency accuracy: ≤ +/- 0.2 ppm calibrated |
| Frequency Deviation | RMS, Min, Max Frequency Deviation | |
| Symbol Clock Error | Symbol Clock Error and Jitter | |
| RX Power Level | RF Generator Output Level Range | VSG output power: +9 to -95 dBm CW 0 to -95 dBm modulated |

DECT (ETSI EN 300 176-1)

| Measurement | Description | Performance |
|---------------------|--|---|
| Power | Normal Transmit Power | VSA power accuracy: ± 0.75 dB (+20 to -35 dBm) ± 0.50 dB (+20 to -35 dBm) typical |
| Power vs. time | Power time template | |
| Frequency offset | Frequency offset | VSA frequency accuracy: ≤ ± 0.2 ppm calibrated |
| Frequency drift | Frequency drift during packet transmission | |
| Frequency deviation | S field, B field, whole packet | |

MIMO System Performance

The additional specifications in the table below apply to the complete IQxel MIMO system

| Parameter | Port Designations | Range |
|------------------------------|-------------------|------------|
| VSA capture trigger accuracy | | ≤ ± 3.5 ns |
| VSA start trigger accuracy | | ≤ ± 3.5 ns |

Port Descriptions

Front Panel

| I/O | Function | Type |
|----------------------------|---|-------------------|
| Power switch | Power on/off | Pushbutton switch |
| RF port 1 | WiFi, Bluetooth input/output | N female |
| RF port 2 | WiFi, Bluetooth input/output | N female |
| RF port 3 (IQxel-280 only) | WiFi, Bluetooth input/output | N female |
| RF port 4 (IQxel-280 only) | WiFi, Bluetooth input/output | N female |
| Power indicator | LED off - AC switch on the back panel is turned off or the AC power cable is not connected LED solid red - test system is in standby mode LED blinking red - test system is powering off LED blinking green - test system is booting up LED solid green - test system is powered on | LED indicator |
| Session active indicator | LED green - remote session active LED red - remote session lock | LED indicator |

| | | |
|---------------------|--|---------------|
| Status indicator | LED green - no faults/errors detected LED orange - Software error detected LED red - Hardware fault detected | LED indicator |
| RF port 1 indicator | LED green - port is a VSA input LED red - port is a VSG output | LED indicator |
| RF port 2 indicator | LED green - port is a VSA input LED red - port is a VSG output | LED indicator |
| USB (2 ports) | USB 2.0 compatible connection to external controller | USB Type A |
| IQ baseband port | Baseband port for IQ Baseband analog signals analysis | SCSI |

Rear Panel

General I/O

| I/O | Function | Type |
|---------------------------|---|--|
| 10 MHz ref input | 10 MHz reference input the 10 MHz - reference input has a 200 ohm impedance and accepts a sine wave ranging in amplitude from 0.3 Vpp to 4 Vpp. | BNC female |
| 10 MHz ref output | 10 MHz reference output | BNC female |
| Marker out / trigger in 1 | TTL compatible | BNC female |
| Marker out / trigger in 2 | TTL compatible | BNC female |
| Marker out / trigger in 3 | TTL compatible | BNC female |
| Marker out / trigger In 4 | TTL compatible | BNC female |
| USB (2 ports) | USB 2.0 compatible connection to external controller | USB Type A |
| AC in | AC power input | 100 to 240VAC (automatically switched) 50 to 60 Hz Includes hard power switch |
| DVI port | Display LitePoint monitor | DVI-D |
| VGA port | Display LitePoint monitor | VGA-15 pin |

Communication I/O

| | | |
|-----|-----------------|-------|
| LAN | 1000 Base-T LAN | RJ-45 |
|-----|-----------------|-------|

General and Environmental

| | |
|---|---|
| Dimensions | Unit with handle: 15.5" W x 3.2" H x 20" D (370 mm W x 82 mm H x 508 mm D) Unit without handle: 14.7" W x 3.2" H x 20.5" D (373 mm W x 82 mm H x 521 mm D) |
| Weight | IQxel-80: 8.25 kg (18.2 pounds); IQxel-160: 9.78 kg (21.6 pounds) |
| Power requirements | 100 to 240 VAC, < 300 W, 50 to 60 Hz |
| Power consumption | <235 W (maximum), <10 W (standby) |
| Recommended PC | Intel Core i5 2.5 GHz with 1 GB of RAM or better |
| Recommended browser for optimal performance | Google Chrome R10 Release |
| Operating temperature | +10°C to +55°C (IEC EN60068-2-1, 2, 14) |
| Storage temperature | -20°C to +70°C (IEC EN60068-2-1, 2, 14) |
| Specification validity temperature | +20°C to +30°C |
| Operating humidity | 15% to 95% relative humidity, non-condensing (IEC EN60068-2-30) |
| EMC | EN 61326 Immunity for industrial environment, Class A emissions |
| Safety | IEC 61010-1, EN61010-1, UL3111-1, CAN/CSA-C22.2 No. 61010-1-12 |
| Mechanical vibration | IEC 60068, IEC 61010 and MIL-T-28800D, class 5 |
| Mechanical shock | ASTM D3332-99, Method B |
| Recommended calibration cycle | 12 months |
| Warranty | 12 months hardware 12 months software updates |

Order Codes

| Code | Product |
|---------------|--|
| 0100-IXEL-001 | <p>IQxel Test System includes:</p> <ul style="list-style-type: none"> • WLAN Measurement Suite Software for SISO 802.11a/b/g/n/p up to 40 MHz channel bandwidth • Graphical User Interface (GUI) with WLAN waveform generation capability • Programming Interface • 1 year hardware warranty |
| 0100-IXEL-002 | <p>IQxel-80 Test System includes:</p> <ul style="list-style-type: none"> • WLAN Measurement Suite Software for SISO 802.11a/b/g/n/p/ac up to 80 MHz channel bandwidth • Graphical User Interface (GUI) with WLAN waveform generation capability • Programming interface • 1 year hardware warranty |
| 0100-IXEL-003 | <p>IQxel-160 Test System includes:</p> <ul style="list-style-type: none"> • WLAN Measurement Suite Software for SISO 802.11a/b/g/n/p/ac up to 160 MHz and 80+80 MHz channel bandwidth • Graphical User Interface (GUI) with WLAN waveform generation capability • Programming interface • 1 year hardware warranty |
| 0100-IXEL-004 | IQxel and IQxel-80 baseband kit, include breakout board, software license and 8x SMB/SMA cables. |
| 0100-IXEL-005 | WLAN MIMO software license for 802.11n and 802.11ac. It also includes 9 BNC connectors and 6 T-connectors. |
| 0100-IXEL-009 | IQxel-160 baseband kit, include breakout board, software license and 16x SMB/SMA cables |
| 0300-IXEL-001 | Bluetooth software license for Bluetooth classic and LE. |
| 0300-IXEL-004 | WLAN 802.11ac software license. |
| 0300-IXEL-009 | ZigBee software license. Includes Zigbee, Z-Wave, and WiSUN. |
| 0300-IXEL-012 | DECT software license. |

Copyright © 2019 LitePoint, A Teradyne Company.

All rights reserved

RESTRICTED RIGHTS LEGEND

No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual, or otherwise, without the prior written permission of LitePoint Corporation.

DISCLAIMER

LitePoint Corporation makes no representations or warranties with respect to the contents of this manual or of the associated LitePoint Corporation products, and specifically disclaims any implied warranties of merchantability or fitness for any particular purpose. LitePoint Corporation shall under no circumstances be liable for incidental or consequential damages or related expenses resulting from the use of this product, even if it has been notified of the possibility of such damages.

If you find errors or problems with this documentation, please notify LitePoint Corporation at the address listed below. LitePoint Corporation does not guarantee that this document is error-free. LitePoint Corporation reserves the right to make changes in specifications and other information contained in this document without prior notice.

TRADEMARKS

LitePoint and the LitePoint logo are registered trademarks of LitePoint Corporation. IQxel is a trademark of LitePoint Corporation. All other trademarks or registered trademarks are owned by their respective owners.

CONTACT INFORMATION

LitePoint Corporation
575 Maude Court
Sunnyvale, CA 94085-2803
United States of America

+1.866.363.1911

+1.408.456.5000

LITEPOINT TECHNICAL SUPPORT

www.litepoint.com/support

Doc: 1075-0022-001
January 2019 Rev 19